

Futronic's FS80 USB2.0 Fingerprint Scanner

Major features and benefit:

Futronic's FS80 USB2.0 Fingerprint Scanner uses advanced CMOS sensor technology and precise optical system to deliver high quality fingerprint image. It can capture an almost un-distorted raw fingerprint image into PC in 100ms. So it is good for any fingerprint recognition application.

Its finger scanning window is a crown glass with a thickness of 14mm. So it is much more reliable and robust compared to any semiconductor type fingerprint sensor.

The finger is illuminated by 4 infra-red LEDs during scanning and the light intensity is automatically adjusted according to scanning fingerprint's characteristics (wet, dry, blurred, etc) to optimize the quality of the captured fingerprint image.

Special electronic circuit is built into FS80 to do Live Finger Detection (LFD). That is, with appropriate software in PC, user can select this LFD feature so that only live finger's fingerprint will be scanned into PC. Fake fingers made from silicone rubber, play-doh, etc, will be rejected. And the LFD feature is included in all Futronic's standard software.



Electrical characteristics

- Light source: Infrared LED
- Supply voltage: DC 4.5-5.5V via USB port
- Power consumption:
 - Active<500mW(during finger scanning)
 - Standby<200mW,
 - sleep mode<5mW
- ESD contact – 8KV no permanent damage
- Air discharge - 16KV no permanent damage

Specification

- Fingerprint scanning window size is 16x24mm
- Image resolution is 480x320 pixel, 500 DPI
- Raw fingerprint image file size is 150K byte
- With Live Finger Detection (LFD) feature
- USB 2.0 compatible interface, plug and play device. WHQL approved for Vista 32&64 bit.
- With a 2M standard USB cable
- Small size, 45 x 63 x 26 mm
- Light weight, 120 gram
- Operation temperature: -10 to +55 C

Futronic provides USB drivers and API for FS80 to capture a raw fingerprint image on the following platforms:

- Windows 2000/XP
- Vista 32bit and 64 bit
- Linux with kernel 2.4 or after (for both x86 and ARM9)
- Windows CE 5.0 and 6.0 (for both x86 and ARM9)

Please download demo programs to try and contact Futronic for more details.

[Futronic Technology Company Limited.](http://www.futronic.com.hk)

Rm1016A, Profit Industrial Bldg. 1-15, Kwai Fung St., Kwai Fong, Hong Kong.

Tel:852-24087705 Fax:852-24082572 web:www.futronic.com.hk email: inquiry@futronic.com.hk